

## CHAPTER 9: ELECTRICAL EQUIPMENTS

9- 1	SPECIFICATIONS ON ELECTRICAL EQUIPMENTS ON BODY .....	9- 1
9- 2	BATTERY .....	9- 2
9- 3	LIGHTING EQUIPMENTS .....	9- 8
9- 4	HEADLAMPS .....	9-10
9- 5	TURN SIGNAL LAMP .....	9-11
9- 6	STOP LAMP SWITCH .....	9-12
9- 9	SPEEDOMETER LAMP .....	9-13
9-10	COMBINATION METER .....	9-14
9-11	FLASHER UNIT (HEAT WIRE TYPE) .....	9-22
9-12	HORN .....	9-24
9-13	WINDSHIELD WIPER .....	9-25



## CHAPTER 9: ELECTRICAL EQUIPMENTS

### 9-1: SPECIFICATIONS ON ELECTRICAL EQUIPMENTS ON BODY

	SEDAN	CUSTOM
<b>Battery</b>		
Type	12N24-3	Same as SEDAN
Capacity	12V/26AH	"
Charging Current	3A	"
Specific Gravity when fully charged (20°C)	1.280	"
Ground Pole	Negative	"
Electrolyte	1.5 ℓ (1.6USqt, 1.3Imp.qt)	"
Turn Signal Relay Type	F1311 Type	"
Turn Signal Frequency	70-90/min at 12±0.2V	"
Oil Level Indicator	Lights at 0.5 ℓ (1 USpt, 0.9 Imp.pt) with car parked	"
Fuel Gauge	F=25 liters (6.6US gal. 5.5 Imp.gal)	F=20 liters (5.3US gal. 4.4 Imp.gal)
	E=2 liters (0.5US gal. 0.4 Imp.gal)	E=2 liters (0.5US gal. 0.4 Imp.gal)
<b>Horn</b>		
Type	BS10-D	Same as SEDAN
Volume	100±5 Phon	"
Current	1.8A	"
<b>Stop Lamp Switch</b>		
Lighting Pressure	4-8 kg/cm <sup>2</sup> (57-114 lb/in <sup>2</sup> )	"
Maximum Current	5A	"
Strength Factor	150 kg/cm <sup>2</sup> (2140 lb/in <sup>2</sup> )	"

#### Windshield Wiper Motor

Mitsuba Denki	
Type	WM-2
Current: Standard Load	Under 1.5A
No Load	Under 1.0A
RPM: Standard Load	33-50 rpm
No Load	45-55 rpm
Motor Torque	Over 60cm-kg